

# specifications

<b>Continuous power output (20Hz—20kHz at 0.05% THD), per channel</b>	
2 channels driven, 8Ω	150W
All channels driven, 8Ω	120W
THD at full rated power	<0.2%
Residual noise & hum	<0.25mV unweighted 20Hz – 22kHz
<b>Inputs</b>	
Phono input:	
Input sensitivity at 1kHz	5mV
Input impedance	47kΩ
Signal/noise ratio (CCIR, 65W)	88dB
Overload margin	31dB
Line inputs:	
Nominal sensitivity	500mV–4V (user adjustable)
Input impedance	47kΩ
Signal/noise ratio (CCIR, 65W)	100dB
<b>Preamplifier outputs</b>	
Max output level	6V RMS
Output impedance	<50Ω
THD+N (20Hz—20kHz)	-100dB
<b>Video inputs</b>	
Component video signal/noise	85dB
Composite video signal/noise	70dB
<b>Headphone output</b>	
Maximum output level into 600Ω	7V
Output impedance	100Ω
<b>General</b>	
Mains voltage	110-120V or 220-240V
Power consumption (maximum)	1kVA
Power consumption (standby)	3VA
Dimensions W x D x H (including feet)	432 x 450 x 180mm
Weight (net)	25.0kg
Weight (packed)	28.0kg
Supplied accessories	mains lead CR102 remote control 4 x AAA batteries manual HDMI lead support bar DAB aerial (if DAB module fitted) FM aerial AM loop aerial setting up microphone
E&OE	
<b>NOTE:</b> All specification values are typical unless otherwise stated.	

### Continual improvement policy

Arcam has a policy of continual improvement for its products. This means that designs and specifications are subject to change without notice.